

Optional “PowerPack”

You can solder a powerful energy buffer to all LokSound V4.0 H0 decoders. In the lower half of figure 14 we show you how to do it. This „PowerPack“ allows your locomotive to keep running for 2 seconds without power.

The PowerPack only operates in digital mode. It automatically turns off on analogue layouts. It may take up to two minutes to fully charge the capacitor („GoldCap“). Therefore, the time bridged with the energy buffer depends on the current draw of your locomotive and the charge-up time. Further information about how to use the PowerPack module is to be found in the “PowerPack module” manual.

