

NMRA Plux 22 Pin Combinations

Plux 8 Pins 7 - 14

	1	2	
	3	4	
	5	6	
f0f	7	8	Motor 1
V+	9	10	Motor 2
Index	11	12	Track Right
f0r	13	14	Track Left
	15	16	
	17	18	
	19	20	
	21	22	

Plux 12 Pins 7 - 18

	1	2	
	3	4	
	5	6	
f0f	7	8	Motor 1
V+	9	10	Motor 2
Index	11	12	Track Right
f0r	13	14	Track Left
LS/A	15	16	AUX1 or f0f
LS/B	17	18	AUX2 or f0r
	19	20	
	21	22	

Plux 16 pins 3 - 18

	1	2	
GPIO/B	3	4	GPIO/A
GND	5	6	V+
f0f	7	8	Motor 1
V+	9	10	Motor 2
Index	11	12	Track Right
f0r	13	14	Track Left
LS/A	15	16	AUX1 or f0f
LS/B	17	18	AUX2 or f0r
	19	20	
	21	22	

Plux 22 Pins 1 - 22

GPIO/C	1	2	AUX3
GPIO/B	3	4	GPIO/A
GND	5	6	V+
f0f	7	8	Motor 1
V+	9	10	Motor 2
Index	11	12	Track Right
f0r	13	14	Track Left
LS/A	15	16	AUX1 or f0f
LS/B	17	18	AUX2 or f0r
AUX4	19	20	AUX5
AUX6	21	22	AUX7